
# MultiPlus Inverter/Charger – 2kW – new models

12 / 24 / 48V - 230 V

www.victronenergy.com




## Multifunctional, with intelligent power management

The MultiPlus is a powerful true sine wave inverter, a sophisticated battery charger that features adaptive charge technology, and a high-speed AC transfer switch in a single compact enclosure. Next to these primary functions, the MultiPlus has several advanced features, as outlined below.

## Parallel operation and three phase capability

Up to six Multis can operate in parallel to achieve higher power output.
In addition to parallel connection, three units can be configured for three-phase output.

## PowerControl - Dealing with limited generator, shore side or grid power

With the Multi Control Panel a maximum generator or shore current can be set. The MultiPlus will then take account of other AC loads and use whatever is extra for charging, thus preventing the generator or shore supply from being overloaded.

## PowerAssist - Boosting the capacity of shore or generator power

This feature takes the principle of PowerControl to a further dimension. It allows the MultiPlus to supplement the capacity of the alternative source. Where peak power is so often required only for a limited period, the MultiPlus will make sure that insufficient shore or generator power is immediately compensated for by power from the battery. When the load reduces, the spare power is used to recharge the battery.

## Four stage adaptive charger and dual bank battery charging for Lithium, Sealed, AGM, Gel and Flooded Batteries

The main output provides a powerful charge to the battery system by means of advanced 'adaptive charge' software. The software fine-tunes the three-stage automatic process to suit the condition of the battery, and adds a fourth stage for long periods of float charging. The adaptive charge process is described in more detail on the Charger datasheet and on our website, under Technical Information. In addition to this, the MultiPlus will charge a second battery using an independent trickle charge output intended for a main engine or generator starter battery.

## High start-up power

Needed to start high inrush loads such as power converters for LED lamps, halogen lamps or electric tools.

## Search Mode

When Search Mode is 'on', the power consumption of the inverter in no-load operation is decreased by approx. 70 %. In this mode the Multi, when operating in inverter mode, is switched off in case of no load or very low load, and switches on every two seconds for a short period. If the output current exceeds a set level, the inverter will continue to operate. If not, the inverter will shut down again.



**MultiPlus 2 kW**
**(bottom cover removed)**

## Programmable relay

By default, the programmable relay is set as an alarm relay, i.e. the relay will de-energise in the event of an alarm or a pre-alarm (inverter almost too hot, ripple on the input almost too high, battery voltage almost too low).

## Remote on / off / charger on

Three pole connector.

## On-site system configuring, monitoring and control

After installation, the MultiPlus is ready to go.
Some settings can be changed with DIP switches.
2 kW models: battery charge voltage / search mode.
For more settings use VE-Config or the VE.Bus Smart dongle.

## Remote configuring and monitoring

Install a Cerbo GX, Ekrano GX or other GX product to connect to the internet.
Operational data can be stored and displayed on our VRM (Victron Remote Management) website, free of charge.
When connected to the internet, systems can be accessed remotely, and settings can be changed.







**Ekrano GX or Cerbo GX**
Provides intuitive system control and monitoring and enables access to our free remote monitoring website: the VRM Online Portal.




**VRM Portal**
Our free remote monitoring website (VRM) will display all your system data in a comprehensive graphical format. System settings can be changed remotely via the portal. Alarms can be received by e-mail or push notification.



**VRM app**
Monitor and manage your Victron Energy system from your smart phone and tablet. Available for both iOS and Android.

| MultiPlus 230V | 12 Volt<br>24 Volt<br>48 Volt | 12/2k/100-32<br>24/2k/60-32<br>48/2k/30-32 |
|---|---|---|
| PowerControl / PowerAssist | | Yes |
| Three Phase and parallel operation | | Yes |
| Transfer switch | | 32 A |
| **INVERTER** | | |
| Input voltage range | | 9,5 – 17 V 19 – 33 V 38– 66 V |
| Output | | Output voltage: 230 VAC ± 2 % Frequency: 50 Hz ± 0,1 % [1] |
| Cont. output power at 25 °C | | 2000 W |
| Cont. output power at 40 °C | | 1800 W |
| Cont. output power at 65 °C | | 1200 W |
| Peak power | | 4000 W |
| Maximum efficiency | | 93 / 94 / 95 % |
| Zero-load power | | 11 / 12 / 13 W |
| Zero-load power in search mode | | 3 / 3 / 3 W |
| **CHARGER** | | |
| AC Input | | Input voltage range: 187-265 VAC Input frequency: 45 – 65 Hz |
| Charge voltage 'absorption' | | 14,4 / 28,8 / 57,6 V |
| Charge voltage 'float' | | 13,8 / 27,6 / 55,2 V |
| Storage mode | | 13,2 / 26,4 /52,8 V |
| Charge current house battery [3] | | 100 / 60 / 30 A |
| Charge current starter battery | | 1 A (12 V and 24 V models only) |
| Battery temperature sensor | | Yes |
| **GENERAL** | | |
| Programmable relay [4] | | Yes |
| Protection [2] | | a – g |
| VE.Bus communication port | | For parallel and three phase operation, remote monitoring and system integration |
| Remote on-off | | On/off |
| DIP switches | | Yes [6] |
| Internal DC fuse | | no |
| Operating temperature range | | -40 to +65 °C (fan assisted cooling) |
| Humidity (non-condensing) | | max 95 % |
| **ENCLOSURE** | | |
| Material & Colour | | Steel (RAL 5012) |
| Protection category | | IP21 |
| Battery-connection | | M8 bolts |
| 230 VAC-connection | | Screw terminals 13 mm² (6 AWG) |
| Weight | | 15,5 kg |
| Dimensions (h x w x d) mm | | 506 x 236 x 147 |
| **STANDARDS** | | |
| Safety | | EN-IEC 60335-1, EN-IEC 60335-2-29, EN 62109-1 |
| Emission Immunity | | EN 55014-1, EN 55014-2, EN-IEC 61000-3-2, EN-IEC 61000-3-3, IEC 61000-6-1, IEC 61000-6-2, IEC 61000-6-3 |
| Automotive Directive | | ECE R10-5 |

1) Can be adjusted to 60Hz and to 240V
2) Protection:
a. Output short circuit
b. Overload
c. Battery voltage too high
d. Battery voltage too low
e. Temperature too high
f. 230 VAC on inverter output
g. Input voltage ripple too high

3) Up to 25 °C ambient
4) Programmable relay which can be set for:
general alarm, DC under voltage or generator start/stop signal function
AC rating: 230 V/4 A
DC rating: 4 A up to 35 VDC, 1 A up to 60 VDC
5) Remote / battery charge voltage / inverter frequency / search mode
6) Battery charge voltage / search mode



**Digital Multi Control Panel**
A convenient and low-cost solution for monitoring and control. With an on/off charger-only switch, full LED readout and a rotary knob to set PowerControl and PowerAssist levels.




**VE.Bus Smart Dongle**
For monitoring and control via Bluetooth together with the VictronConnect app. It also measures battery voltage and temperature.



**Interface MK3-USB**
Needed to configure the MultiPlus. Can be used with the VictronConnect app or VEConfigure software. The interface connects to the MultiPlus via an RJ45 UTP cable and plugs into a USB port.




**VictronConnect app**
Use to monitor or configure the MultiPlus using your phone tablet or PC.



**Battery Monitor**
To monitor battery state of charge via Bluetooth or the VRM portal.
The BMV 712 Smart has display, while the SmartShunt does not have a display. Both communicate via Bluetooth and have a VE.Direct communication port.

Victron Energy B.V. | De Paal 35 | 1351 JG Almere | The Netherlands
E-mail: sales@victronenergy.com
**www.victronenergy.com**