

# Cegasa E/Scal 6

## Manufacturer links

- Product page: [Cegasa E/Scal 6](#)
- Datasheet: [TDS E/Scal 6 \(English, Nov 2025\)](#)

## Use with the HS19 (650 - 1000 V DC)

- Modules per stack: **13 - 15** (the product allows 3 - 15, but fewer than 13 modules sits below the HS19 input range)
- Usable voltage range: **676 - 940 V**
- Capacity: **75 - 86 kWh** per stack

## Full product specifications (unverified, from manufacturer datasheet)

- Module: 57.6 V nominal, 5.76 kWh (~100 Ah)
- Up to 4 strings in parallel (max 60 modules, 345 kWh)
- Recommended current 50 A, max 63 A continuous, 100 A peak (<1 min)
- Note: E/Scal 6 is the renamed continuation of the E/Scal HV; certificates may still reference the old name

## Compatibility status

- Test status: tested and running in field tests

## Setup guide

Contact battery manufacturer for setup instructions.

From:  
<https://www.victronenergy.com/live/> - **Victron Energy**

Permanent link:  
[https://www.victronenergy.com/live/hv\\_battery\\_compatibility:cegasa?rev=1781682783](https://www.victronenergy.com/live/hv_battery_compatibility:cegasa?rev=1781682783)

Last update: **2026-06-17 09:53**

