

# Navico MFD Integration

## 1. Introduction

Navico is behind the B&G, Simrad and Lowrance brands.

## 2. Compatibility

	Product	Display Size						Comments
Simrad	NSO EVO3				16	19	24	
	NSO EVO2				16	19	24	
	NSS EVO3	7	9	12	16			
	Go	7*	9	12				5 is not compatible; no Ethernet port; *Go7 XSE not compatible – only Go7 XSR
B&G	Zeus3 Glass Helm				16	19	24	
	Zeus3	7	9	12	16			
	Vulcan	7	9	12				
Lowrance	HDS Live	7	9	12	16			
	HDS Carbon	7	9	12	16			
Information display	IDS		9	12				

## 3. Wiring

The Navico device needs to be connected to the Venus-device using Ethernet. Its not possible to connect over WiFi. For the ethernet connection, a Navico adapter is required:

- ETHADAPT-2M 127-56

## 4. Configuration

### Venus-device settings

1. Go to Settings → Services, and there enable MQTT.
2. Go to Settings → System Setup → Scroll to the bottom → Battery measurements. And there set

up what batteries you want to see on the MFD; and by what name.

## Networking

No settings are necessary. The Venus-device and the Navico devices connect to each other using a technology called linklocal addressing.

It is possible to connect the a router to the same LAN; and that way provide for internet access.

## 5. Usage

TBD add screenshots and so forth.

From:

<https://www.victronenergy.com/live/> - **Victron Energy**

Permanent link:

<https://www.victronenergy.com/live/venus-os:mfd-navico?rev=1552949634>

Last update: **2019-03-18 23:53**

